



Model Number X3906

Lowpass Filter

Rev.-
01/18/07

Features:

- Coaxial Design
- Low Loss

Applications:

- Communication
- Data
- Test Equipment

Package size:

- 0.5 x 0.9 x 5.0"

(Please see outline for exact dimensions)



Specifications: (+25C)

Passband	1 to 8000 MHz
Insertion Loss	1.0 dB
VSWR	2:1
Rejection	50 dB from 9500 to 10500 MHz
Rejection	65 dB from 10501 to 20000 MHz
Connectors	SMA Female

Delta Microwave

1301 Vanguard Dr.
Oxnard, CA. 93033

Phone: 805.240.1044
Fax: 805.240.9544

email: sales@deltamicrowave.com
www.deltamicrowave.com

--	--

By

Checked